


Eurorack Adapter for L6 **ERL-6** **EN**

Included items




Rack mounting plates

Dimensions: 126.8 mm (W) × 128.5 mm (D) × 44 mm (H)
Weight: 147 g (left), 137 g (right)



Ribbon cable

Length: 300 mm
Weight: 13 g



Power adapter

Dimensions: 65 mm (W) × 34 mm (D) × 26.6 mm (H)
Weight: 22 g
Rated input: +12 V \equiv 1.6 A
Rated output: +5.6 V \equiv 2.5 A




Screws × 8

(including 2 extra screws)


Attachment procedures

Remove batteries from the L6 before attaching the ERL-6.
Leaving batteries in for a long time could lead to leaking and cause malfunction.


- 1** Loosen the screw and lower the clasp.




- 2** Insert the plate into the 2 connection openings on the L6.




- 3** Close the plate toward the L6.




- 4** Raise the clasp until it clicks into place. Then, tighten the screw.
Repeat these procedures to attach the other plate.




- 5** Attach the power adapter and tighten the two screws.




- 6** Connect the ribbon cable to the power adapter.



- 7** Connect the ribbon cable to a connector in the Eurorack case.



- 8** Tighten screws in four places to install into the Eurorack case.



Video manual access
zoomcorp.com/help/erl-6

- Always stop the power supply to the Eurorack case before installation.
- The power adapter converts +12 V to +5.6 V to power the L6. With a +12 V power supply, it consumes a maximum of 500 mA. Use a Eurorack case that is compatible.
- Do not connect the power adapter to anything other than a compatible product. Doing so could cause malfunction.

ZOOM CORPORATION 4-4-3 Kanda-surugadai, Chiyoda-ku, Tokyo 101-0062 Japan zoomcorp.com

© 2024 ZOOM CORPORATION Copying or reprinting this manual in part or in whole without permission is prohibited. You might need this manual in the future. Always keep it in a place where you can access it easily. The contents of this document and the specifications of the product could be changed without notice.

Z21-5503-01